



NOVOHALL Rotary Sensor touchless transmissive

Series RFX-6900







Inhalt

Mechanical Data	3
Characteristics	4
Technical Data Analog Interface	5
Ordering Specifications	6
Technical Data CANopen Interface	7
Ordering Specifications	8
Accessories	
Position marker / Concer mounting	
Position marker / Sensor mounting	8
M8 Connector System	12



Mechanical Data



 (20°) (20°)

Mechanical data		
Dimensions	see deminsion drawing	
Mounting	with 3 screws M4, screwing min. 7 mm	
Fastening torque of mounting screws	2.5 ±0.5	Nm
Mechanical travel	360 continuous	0
Maximum operational speed	mechanical unlimited	
Weight (without connection)	approx. 200	g
Environmental Data		
Operating temperature	-40+85	°C
Vibration IEC 60068-2-6	52000 Amax = 0,75 amax = 20	Hz mm g
Shock IEC 60068-2-27	50 (6 ms)	g
Protection class (DIN EN 60529)	IP67 connector output M12 IP6K9K cable output	



CAD data see www.novotechnik.de/en downloads/cad-data/



Characteristics





Technical Data Analog Interface

- Current



Electrical Data	RFX-69 32 analog Current	
Output signal	4 20 (burden max. 250 Ω, higher on request)	mA
Number of channels	1/2	
Update rate	5	kHz
Resolution	12	Bit
Measuring range	60, 120, 180, 240, 300, 360	0
Independent linearity	0.5	±%FS
Interlinearity channel 1 to channel 2 at measuring range < 90° Interlinearity channel 1 to channel 2 at measuring range $\geq 90^{\circ}$	4.0 2.0	±%FS ±%FS
Repeatability	0.2	0
Hysteresis at measuring range < 360° Hysteresis at measuring range 360°	0.1 0.25 (lower hysteresis on request)	0
Temperature error at measuring range < 90° Temperature error at measuring range ≥ 90°	200 160	ppm/K ppm/K
Supply voltage Ub	12/24 (9 34)	VDC
Current consumption (w/o load)	typical 20 per channel, supply voltage Ub = 24 V	mA
Reverse voltage	yes	
Short circuit protection	yes, all oututs vs. GND and Ub	
Insulation resistance (500 VDC)	≥ 10	MΩ
Cross-section cable	0-5 (AWG 20)	mm ²
Environmental Data		
EMC compatibility	ISO 10605 Packaging und Handling + Component Test (ESD) 8 kV, 15 kV ISO 11452-2 Radiated EM HF-fields, Absorber hall 100 V/m ISO 11452-5 Radiated EM HF-fiels, stripline 200 V/m CISPR 25 Radiated Emission, class 5 ISO 7637-2 Pulse 1, 2a, 2b, 3a, 3b, 4, 5 SG 4 ISO 7637-3 Transient emssion SG 4 Interference emission and immunity according to ECE-R10 (E1)	
Functional safety	Suitable for safety-relevant applications according to ISO 13849 after customer validation. Further safety data and support for functional safety are available on request.	
MTTF (DIN EN ISO 13849-1- parts count method, w/o load, wc) MTTFd (DIN EN ISO 13849-1 parts count method, w/o load, wc) MTTF certificates bittes://www.powdechnik.de/en/downloads/certificates/	46 (per channel) 92 (per channel) httd-certificates/	years years

Single channel version Cable (Code -252) M12 connector (Code -551) Supply Ub GN Pin 1 GND BN Pin 3 Pin 2 Signal WH Not assigned YE Pin 4 Partly redundant version Cable (Code -252) M12 connector (Code -551) Supply Ub GN Pin 1 GND BN Pin 3

WH

YE

Pin 2

Pin 4

Fully redundant version			
	2 x cable (Code -352)	2 x M12 connector (Code -651)	
Supply Ub 1	Channel 1 / GN	Channel 1 / Pin 1	
GND 1	Channel 1 / BN	Channel 1 / Pin 3	
Signal 1	Channel 1 / WH	Channel 1 / Pin 2	
Supply Ub 2	Channel 2 / GN	Channel 2 / Pin 1	
GND 2	Channel 2 / BN	Channel 2 / Pin 3	
Signal 2	Channel 2 / YE	Channel 2 / Pin 4	
not assigned	Channel 1 / YE Channel 2 / WH	Channel 1 / YE Channel 1 / Pin 4 Channel 2 / WH Channel 2 / Pin 2	

Signal 1

Signal 2



Ordering Specifications Analog Interface - Current





Technical Data

Type Designations	RFX-69214-6	
	CANopen	
Electrical Data		
Measured variables	Position and speed	
Measuring range	360	0
Measurement range speed	0 1600	min-1
Number of channels	1/2	
Output signal / protocol	CANopen protocol to CiA DS-301 V4.2.0, Device profile DS-406 V3.2 Encoder Class C2, LSS services to CiA DS-305 V1.1.2	
Programmable parameter	Position, speed, cams, working areas, rotating direction, scale, offset, node-ID, baud rate	
Node-ID	1 127 (default 127)	
Baud rate	50 1000	kBaud
Resolution across 360° (position)	14	bit
Resolution speed	360/2 ¹⁴ ≈ 0.022	°/ms
Update rate	1	kHz
Independent linearity	≤ 0.5	±% FS
Repeatability	≤ 0.36	0
Hysteresis	≤ 0.36	0
Temperature error	0.2	±% FS
Supply voltage Ub	12/24 (8 34)	VDC
Current consumption (w/o load)	< 100	mA
Reverse voltage	yes, supply lines	
Short circuit protection	yes, output vs.GND and supply voltage Ub (up to 40 VDC)	
Overvoltage protection	< 45 (permanent)	VDC
Insulation resistance (500 VDC)	≥ 10	MΩ
Cross-section cable	0.5 (AWG 20)	mm ²
Bus termination internal	120, optionally	Ω
Environmental Data		
Operation temperature	-40 +105 (-25 +85 with M12 connector)	°C
MTTF (DIN EN ISO 13849-1 parts count method, w/o load, wc)	one-channel: 71 / two-channel: 58 (per channel)	years
Functional safety	If you need assistance in using our products in safety-related systems, please contact us	
EMC compatibility	ISO 10605 Packaging and Handling + Component Test 8 kV ISO 11452-2 Radiated EM RF fields, Absorberhall 100 V/m ISO 11452-5 Radiated EM RF fields, Stripline 200 V/m CISPR 25 Radiated emission class 3 ISO 7637-2 Pulse 1, 2a, 2b, 3a, 3b, 4, 5 SG 3 ISO 7637-3 Transient transmission SG 4 EN 13309 Construction machinery Interference emission and immunity according to ECE-R10 (E1)	

Connection assignment

Signal	Cable Code 2 / 3	Connector M12 Code 5 / 6
CAN_SHLD	Shield	pin 1
Supply voltage Ub	BN	pin 2
GND	WH	pin 3
CAN_H	GN	pin 4
CAN_L	YE	pin 5

Cable shielding connect to GND.



Ordering

Specifications





Position Marker Mounting Material





Position Marker Mounting Material





Z-RFC-P02 / -P04 / -P08 / -P20 / -P23	Z-RFC-P18	
0.3 3.5	0 2.5	
0.8 4	0 3	
0.3 3.5	0 2.5	
	Z-RFC-P02 / -P04 / -P08 / -P20 / -P23 0.3 3.5 0.8 4 0.3 3.5	Z-RFC-P02 / -P04 / -P08 / -P20 / -P23 Z-RFC-P18 0.3 3.5 0 2.5 0.8 4 0 3 0.3 3.5 0 2.5

Mounting instructions Z-RFC-P04

- In general, we recommend mounting on not magnetizable materials, otherwise the stated working distances can change
- If the shaft is magnetizable please keep sufficient distance
- When the magnet is mounted in the shaft, the shaft may not be magnetizable
- If the magnet is axially fixed on a magnetizable shaft the working distances reduces by approx. 20%

Lateral magnet offset



Lateral magnet offset will cause additional linearity error. The angle error, which is caused by radial displacement of sensor and position marker depends on the used position marker or magnet type.

Additional error (°) at radial displacement

Interface	Z-RFC-P02 / P04 / P08 / P20 / P23			Z-RFC-P18		
	0.5 mm	1 mm	2 mm	0.5 mm	1 mm	2 mm
Analog (current)	0.7	1.8	5.2	1.1	2.0	4.6
CANopen one-channel	0.4	1.1	3.5	0.7	1.3	3.3
CANopen two-channel	0.7	1.8	5.2	1.1	2.0	4.6



Accessories

Connector System M12





Accessories Connector System M12

